

AUTOMATIC VOLTAGE REGULATOR (STABILIZER)

Power Star Series (2-steps Regulation/ Wall Mounting Type)



- › Provide stable output voltage through boost and buck stabilizer
- › Eight output receptacles Nema5-15R or Universal Nema type
- › Built-in thermal switch for over-temperature protection
- › Provide overload and short circuit protection
- › Fire retardant plastic material
- › Wall mounting holes

MODEL	I-131-1000	I-131-1500	I-131-2000
CAPACITY	1000VA/500W	1500VA/750W	2000VA/1000W
INPUT			
Voltage	110/115/120Vac or 220Vac		
Voltage Range	110/115/120Vac: 92-138Vac ; 220Vac: 184-276Vac		
Frequency Range	50/60Hz		
OUTPUT			
Steps of Regulation	2-steps (1-step Boost & 1-step Buck)		
Output Receptacles	Nema5-15R or Universal Nema: 8pcs AVR regulated plus surge protected		
Protection	Overload / short circuit: Manual reset circuit switch		
	Over-temperature: Thermal switch		
	Surge protection: 175 Joules		
INDICATORS			
Power On/Off LED	Green		
Boost LED	Yellow		
Buck LED	Yellow		
ENVIRONMENT			
Humidity	0-95%(Non-condensing)		
Noise Level	Less than 40dB at 1M		
PHYSICAL			
Dimension	265*110*95mm		

*Product specifications are subject to change without further notice.