

AUTOMATIC VOLTAGE REGULATOR (STABILIZER)

Power Star Series (3-steps Regulation / 8 Receptacles)



- › Provide stable output voltage through boost and buck stabilizer
- › Built-in thermal switch for over-temperature protection
- › Provide modem / phone line surge protection
- › Provide overload & short circuit protection
- › User-friendly visual LED indicators
- › Anti-flammable plastic housing
- › Accept wide input range

MODEL	PS-800	PS-1200	PS-2000
CAPACITY	800VA/400W	1200VA/600W	2000VA/1000W
INPUT			
Voltage	110/115/120Vac or 220Vac		
Voltage Range	110/115/120Vac: 90-144Vac ; 220Vac: 161-288Vac		
Frequency Range	50/60Hz		
OUTPUT			
Steps of Regulation	3-steps(2-steps boost & 1-step buck)		
Output Receptacles	8pcs Nema 5-15R Outlet		
Protection	Overload / short circuit: Manual reset circuit switch		
	Over-temperature: Thermal switch		
	Surge protection: 175 Joules		
INDICATORS			
Power On/Off LED	Green		
Boost/Buck LED	Yellow		
ENVIRONMENT			
Operating Temperature	0°C-40°C(32°F-104°F)		
Humidity	0-95%(Non-condensing)		
Noise Level	Less than 40dB at 1M		
PHYSICAL			
Dimension	245*89*87mm		

*Product specifications are subject to change without further notice.